

Joey Lite MKII

4" fully customizable wall mounted touch screen control system. Controls IR and RS232 using the supplied Access Port breakout box. Simple CAT5 to RJ45 connection. Includes Power Supply.



A new concept in inexpensive, flexible control systems, Joey Lite is effectively a touchscreen without the LCD screen. Instead, you design your own layout in landscape or portrait using the simple drag and drop style Joey authoring program. Print the result on high resolution paper, cut it out and slide it into the slot under the glass touchscreen. Joey Lite will light it using state of the art fibre optic backlighting.

Joey Lite will save you time by simplifying your technology.

Joey Lite will save you money by managing your equipment. Joey Lite is smart enough to know when a room is empty and will shut the room down. This is especially important where projectors are installed. The Joey Lite does this by tracking time, key presses and room movement.

Programmable LEDs on each button indicate the mode your system is in.

Joey Lite can directly control your equipment via Infra Red and RS232. It comes with an Access Port to simplify the wiring and allow a neater finish to the installation. Joey Lite can be a complete control solution by itself.

Joey Lite is simple to install – it's designed for surface installation with minimal cut out requirements.

Panel Type	Field replaceable underlay, fibre optic LED backlight.
Panel Size	4.0" diagonal
Effective Viewing Area	80 (W) x 60 (H) mm (landscape mode)
Touchscreen	Digital 4 x 6 Matrix touchscreen overlay with audio feedback
Thickness	2.00mm
Type	Anti-scratch ITO Film over glass
Front Bezel Dimensions	143 x 115 x 12 mm
Power Supply	12VDC 50mA (depends on no. of LEDs lit)
Software	Joey Authoring Program
Connectivity	Connects to Access Port Via single Cat5
Programming port (3.5mm Jack)	x 1
IR Bus RJ45	x 1