

IR Relay Box

Four relays, single pole double throw.
Controlled by any of the CommBox control units, or via RS232.



Four power-rated changeover relays

May be used for controlling lights, screens, curtains etc.

Can perform power, low voltage or signal switching

Standard DIN rail mounting enclosure

IR or RS-232 controllable

Commands for ON, OFF, Toggle and Momentary control

Addressable. Up to 16 "Simple range" products can co-exist on the same system

Internal power supply can power small control panels (e.g. Joey wallmount, door entry panel) and IR receivers

Indicator LEDs display relay status

Moulded power plug/socket (supplied) avoids accidental wrong connections and enhances safety

Enclosure	Standard ABS, DIN rail mounting, 3 unit
Number of relays	Four
Type of relays	Single pole changeover
Relay switching voltage (max)	250 volts
Relay switching current (max)	10 mps
Relay connections	3 pin pluggable screw terminals
Power input	220 – 240 volts AC 50-60Hz
IRBus power output	12 volts (nominal) @ 250mA max- Over current protected with internal self-resetting polyfuse.
Dimensions	86mm(H) x 69mm(W) x 60mm(D)